

# eSynC-vc2UE-F *Product/Green Sheet*

## Fast-Charging SimulCharge™, Voltage Converter, Ethernet, 2 x USB Adapter with RBM Technology for USB-C Mobile Devices

The eSynC-vc2UE-F is a fast-charging SimulCharge™ adapter designed for use with select USB-C mobile devices. It features simultaneous charging and access to data, a built-in voltage converter, wired Ethernet connectivity, two USB-A ports for connecting USB peripherals and Network Recovery & Battery Modulation (RBM) technology.

The eSynC-vc2UE-F's on-board DC-DC voltage can take a power input of between 12 and 36 volts\* and can provide either 9-volt fast charging or the standard 5-volt charging to compatible mobile devices. The adapter can be used to supply power in permanent and semi-permanent installations (adhering to local electrical codes) with minimal installation cost. This eliminates the requirement for a licensed electrician to install and run a dedicated AC power line.

When a 36-volt power supply is used, you also get a distance power advantage. This means it can be installed in locations with limited electrical outlets and provides greater options for mobile device placement.

The eSynC-vc2UE-F's Ethernet port provides a reliable 10/100-capable wired network connection and its USB-A ports allow you to connect up to two peripherals, such as a scanner and printer. It is ideal for running mobile POS systems, company management systems or digital signage in a 24-hour environment.

Battery Modulation protects the mobile device from overcharging and its battery from bloating, which can cause severe damage to the device. Together with the LAVA Tablet Manager (LTM) app, which needs to be installed on the mobile device, the adapter optimizes battery life and makes the mobile device last longer for a better return on investment. LTM monitors the battery level and users can set upper and lower charging thresholds for the battery. When the battery charges to the higher threshold, the adapter turns off charging and the mobile device is allowed to discharge until it hits the lower threshold. This ensures the battery never overcharges, even if it is left plugged in 24/7. This modulation and overcharge protection helps to extend the lifespan of both the battery and device.

Network Recovery provides a failsafe system to recover the wired network connection if it drops out. If the connection is lost for more than a few minutes, the LTM app sends a command to reset the Ethernet portion of the adapter to re-establish the connection. It's the equivalent of unplugging the Ethernet cable and then plugging it back in.

The adapter comes in a black ABS casing that protects the electronics from mild shocks and impacts, allowing it to be used in different implementations. It does not ship with the USB-C to USB-C cable required to connect the adapter to the mobile device. This cable can be purchased separately from LAVA or a third-party supplier.

*\*The 12-36V DC power supply is not included with the adapter and must be purchased separately.*

